

Extender


EXT-01



EXT-01 can be used as a range extender for the Plejd mesh and as an input device to wirelessly control other products from Plejd. It can also be used as a battery backup for the system with the integrated BAT-01.

- Extends the range by being part of the Plejd-mesh.
- Maintains time functions, such as astro schedule, in the event of a power outage (BAT-01 is integrated).
- Control other products from Plejd wirelessly using a push button or Plejd accessories such as Rotary adapter (RTR).

Install the product in the appliance box behind the push button/box lid or secure it with a Mounting clip (MNT-01, not included) on the wall or DIN rail.



MAINS ELECTRICITY

230 V/50 Hz, max 0.02 A

STANDBY POWER

0.2 W

EXTERNAL OPERATING TEMPERATURE

-25 to +35 °C

CALCULATED BATTERY LIFE

10 years reserve

DIMENSIONS

46x46x18 mm

CABLE AREA

Connections: 0.5–4.0 mm²

PROTECTION

Overheating – software

RADIO

2.4 GHz mesh
Bluetooth®
<10 dBm

RADIO RANGE

Approx. 10 m indoors.
The Plejd mesh technology extends the range by allowing the units to communicate with each other.

